

# Cubiscan 110

---

For a Cubiscan® 110 cubing and weighing system

For yderlig information

Venligst kontakt Zolvo ApS mail: [AFL@zolvo.eu](mailto:AFL@zolvo.eu)



# Cubiscan 110

---

## Introduktion:

Produktet Cubiscan 110 er forhandlet i Danmark, Sverige og Finland af Zolvo ApS. Udstyret udregner automatisk længde, bredde, højde og vægt på regulære vare eller kasser.

## Produkts beskrivelse:

Til genstande indenfor vægt og dimension, denne alsidige model anvender ultralyd fra 3 sensor, og har 3 vægt celler fordelt i hvert hjørne af skanneren. Skanneren anvendes oftest i traditionelle distribution miljø til at indgive master data om varernes kvadret forme volumen fylde.

Cubiscan 110 giver dig total kontrol i shipping processen. Det giver dig mulighed for hurtigt og konsekvent at indsamle produktoplysninger (vægt og størrelse) - der er ikke behov for et ekstra værktøj, ingen plads til menneskelig fejl, ingen grund til at indtaste data og ingen fejldata. Og oplysningerne overføres let til dit databehandlingsystem, hvor det kan bruges med det samme. Cubiscan 110 volume og vejningsenhed betjenes i forbindelse med en leveret eller egen laptop / pc, men kan også bruges som en selvstændig enhed i kraft af det integrerede LED display og kontrolpanel.

Det maksimale måleområde af regelmæssige formede genstande er på 750 x 600 x 900 mm, hvor der anvendes af infrarøde sensorer. Den har en vægtpacitet på 50 kg. Dimensioner måleopløsning er 2 mm. Vægttolerancen er på 20 g.

Hver enhed har fire aktive kommunikationsporte. Cubiscan 110 kan betjenes i en fast position eller kan udstyres med en vogn og bærbar strømforsyning til fuldstændig mobil drift. Cubiscan 110 benytter avanceret sensorteknologi, der er sikker for operatører og fragt, og kan integreres direkte med strekcode etiket scanning og udskrivende enheder.

Et års fabriksgaranti på dele og arbejdskraft er inkluderet, en vedligeholdelsesaftaler er muligt og en udvidede garanti hvor der opnåes op til 3 års garanti er også en mulighed.



# Cubiscan 110

## Cubiscan 110 specifikationer:

### Fysiske specifikationer:

Længde	112 cm
Bredde	81 cm
Højde	119 cm

### Ydeevne:

Længde	75 cm
Bredde	60 cm
Højde	90 cm
Volume tolerance	2 mm
Max vægtkapacitet	50 kg
Vægt tolerance	20 gram

### Yderlige information:

Data output	Serial RS-232, Ethernet and USB
Volume sensor	Ultralyd
Vægt sensor	4 vægt sensor
Brugergrænseflade	Integreret display og tastatur /Qbit software
Strømkraft	95 - 250 v, 47-63 Hz
Drift temperatur	-10 til 40 grader
Fugtighed	0 - 90% ikke kondenserende



# Cubiscan 110

## Oftest anvend software:

Qbit-DB er vores mest populære version af software, der ligger på en bærbar pc eller laptop, der er forbundet med Cubiscan. Den indfanger data lokalt og sender derefter informationen via FTP eller til den udpeget folder. Alternativt kan dataene eksporteres manuelt til en hvilken som helst folder. QbitDB tilbyder også funktionaliteten til at optage billeder af produktet, der måles.

Sequence	Item Number	Pack Type	Description	Length	Width	Height	Weight	Volume	Dim Wgt	Dim Unit	Wgt Unit	Vol Unit	Factor	Site Id	Date-Time
1	11111111			2	2	2	10	8	0	mm	gr	mm	7009	19/01/2010 12:03:33	
11	1234			244	124	76	92	229456	0.3834	mm	gr	mm	5937	02/02/2010 10:10:09	
3	12345	AA01		1	1	1	1	1	0	mm	gr	mm	7009	21/01/2010 11:28:35	
4	12345	AA02													
5	12345	AA03		86	44	9	70	34056	0.0057	mm	gr	mm	5937	02/02/2010 09:44:14	
9	12345	AA04													
2	123456			19.5	19.5	10	148	3802.5	0.0005	mm	gr	mm	7009	19/01/2010 12:21:34	
6	123456	BB01													
7	123456	BB02													
8	123456	BB03													
10	210827			26	30	19	70	14820	0.0025	mm	gr	mm	5937	02/02/2010 09:44:52	
12	210828			229	39	16	90	142896	0.0238	mm	gr	mm	5937	02/02/2010 11:35:27	

Qbit-Xfer tillader, at data fra Cubiscan 110 overføres direkte til en kundes tilknyttet åbne program. Denne version af software er designet til kunder, der har et Windows-baseret system.

# Cubiscan 110

---

## **KOMMUNIKATION:**

Cubiscan 110 overfører længde-, bredde- og højde data samt andre diagnostiske data via EIA RS232-C kommunikationsprotokol. Dataene består af serielt kodede ASCII-tegn.

## **GARANTI:**

En 12 måneders reservedelsgaranti er inkluderet i købsprisen. Denne dækning giver mulighed for udbedring af problemer via telefon/teamviewer/onsite og eventuelt udskiftning af defekte dele.

## **DOKUMENTATION:**

Hver cubiscanner leveres med:

- En kopi af operatørens instruktioner.
- En kopi af operatørens instruktioner er tilgængelig online.

## **LAPTOP & PC KRAV:**

Alle versioner af Qbit software er designet til at fungere med følgende minimum computer krav.

Processor PC Pentium III processor eller bedre.

Hukommelse 256 MB RAM.

Harddisk 40 MB diskplads tilgængelig.

Skærm VGA 1024 x 768 opløsningsfarvevisning.

Operating System Windows 98, Windows NT, Windows 2000, Windows XP eller nyere.

Cubiscan enheden monteres til computeren via USB eller seriel forbindelse. Håndscanneren forbindes via en PS / 2-port eller USB-port.



# Cubiscan 110

## CUBISCAN NEW PRODUCT LIMITED WARRANTY

**Statement of Warranty.** Subject and according to the Terms and Conditions set forth below, Quantronix, Inc., (hereafter referred to as “Quantronix”) warrants to the Buyer that its new product is in accordance with Quantronix published specifications (or those agreed upon with Buyer in writing) at the time of sale or lease, and that such product shall be free from defects in material and workmanship for a period of **one year** from, as applicable: the date of sale or the Commencement Date under a written equipment lease or rental agreement (the “Warranty Period”). For purposes of this warranty, the term “Buyer” shall mean and refer only to the party which originally – whether from Quantronix directly, or from a distributor, agent or reseller authorized by Quantronix – purchases, or leases under a written equipment lease or rental agreement, the Quantronix product which is the subject of this warranty.

**Terms and Conditions of Warranty.** This warranty is applicable exclusively to original equipment products, and components which were manufactured by Quantronix. Quantronix does not warrant, for any purpose, any part or component manufactured by another manufacturer, nor which is used or rebuilt. Quantronix’ obligation and liability under this warranty is expressly limited to repair or replacement (at its option) of the warranted equipment or components within the Warranty Period. A purchase by Buyer of equipment which it had first leased or rented shall not start a new Warranty Period.

In the event of the occurrence of a claim under this warranty, the Buyer shall have a duty to promptly notify Quantronix in writing of the nature and specifics of the claimed defect. Failure to so notify shall void this warranty. Any claim of a warranted defect is subject to inspection and analysis by Quantronix to conclusively identify or confirm the nature and cause of failure and application of this warranty. Any defective components, mechanical or electrical, will be repaired or replaced, at the discretion and authorization of Quantronix, at Quantronix’ facilities in Utah. It shall be the Buyer’s responsibility to return the faulty equipment or components to Quantronix at Buyer’s expense. Quantronix’ obligation shall not include transportation charges, nor labor, material, or service charges involved in the removal, return or installation of equipment or components.

Except as provided herein, Quantronix shall have no other obligation or liability due to defective equipment or components. Accordingly, but without limitation, Quantronix shall not be liable for: losses, injury or damage caused to persons or property by Quantronix products or their failure; indirect, special or consequential damages of any nature including but not limited to loss of profit, delays or expenses, such as those arising from the use of or inability to use the products; nor any incidence of personal injury or property damage arising from the negligence or willful act of anyone other than itself or its employees.

Quantronix reserves the right to incorporate improvements in material and design of its products without notice and is not obligated to incorporate the same improvements in equipment previously manufactured.

**Conditions Which Void Warranty.** This agreement shall not apply to equipment or components which has/have:

- A. Been the subject of repairs or modifications not authorized by Quantronix.
- B. Not been operated under normal use and service according to that for which it was intended.
- C. Not been operated or maintained in accordance with Quantronix’ printed instructions.
- D. Been subject to misuse, negligent handling, improper installation, accident, damage by fire, submersion, or act of God.
- E. Had serial numbers altered, defaced or removed.
- F. Been sold, loaned, leased, subleased or in any other way transferred to or placed within the control of any party other than the Buyer.
- G. Been operated beyond capacity.

THE FOREGOING IS IN LIEU OF ALL OTHER REMEDIES, GUARANTEES, LIABILITIES OR WARRANTIES. QUANTRONIX MAKES NO OTHER WARRANTY, EXPRESS OR IMPLIED, AND MAKES NO WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE. This statement sets forth the full extent of Quantronix’ liability for breach of any warranty or deficiency in connection with the sale or use of the product. No employee or representative of Quantronix is authorized to change this warranty in any way or grant any other warranty.